

	1	2	3	4	5	6	7	8	9			
REV.	REMARK	DATE	SIGN.									
									<b>RoHS</b>			
<p><b>Material RoHS Compliant:</b></p> <p>1. Cable:</p> <p>CONDUCTOR: 30 AWG SOLID SILVER PLATED COPPER.          INSULATION: SKIN-FOAM-SKIN          PAIR: 2 WIRES, WH AND YE PARALLEL.          CORE: 8 PAIRS          PAIR DRAIN WIRE: #0.2mm (32AWG) TINNED COPPER.          PAIR SHIELD: ALUMINUM FOIL OVERLAPPED, ALU INSIDE.          INNER SHIELD: ALUMINUM FOIL OVERLAPPED, APPLIED LONGITUDINALLY.          OUTER SHIELD: 0.1mm DIA TINNED COPPER BRAID, 85% COVERAGE.          DIAMETER: 6.1 ± 0.2 mm          PRINT LEGEND: "LEONI High Speed Cable ParaLink®-14 100Q 8pairs 30AWG (SHIELDED)(UL) E116441 CL2 75°C"          DIFFERENTIAL IMPEDANCE: 100±5 OHM.</p> <p>2. Connector:</p> <p>P1,P2: 4x-Pluggable-QSFP(SFF-8436)          (1) P.C.B: 4 LAYERS, GOLD PLATING ON CONTACT PADS.(SPCB-040112A, AC Coupling)          (2) Latch: Stainless Steel with Pull Tab.          (3) Backshell: Zinc Die Casting Hood/ Nickel Plating.</p> <p>3. For FDR 14G USE.</p> <p>4. Two-Wire Serial Memory: Atrmel AT24C02B EEPROM(256 Bytes), Digital monitoring &amp; control function and memory page not supported.</p>												
DESC. QSFP FDR 14G Cable Assembly				APPROVED	CHECKED	DESIGNED	TOLERANCE	SCALE	#	UNIT	mm	
P/N UA55-RC005982 CUSTOMER P/N						Sino		DATE	01/23/13	DWG NO.:	DWG\RC\5982	

	1	2	3	4	5	6	7	8	9																																																																																																																								
REV.	REMARK	DATE	SIGN.																																																																																																																														
<b>WIRING DIAGRAM</b>																																																																																																																																	
<table border="1" style="width:100%; border-collapse: collapse;"> <thead> <tr> <th colspan="4">HIGH SPEED SIGNAL</th> </tr> <tr> <th colspan="2">P1(4x-Pluggable-QSFP)</th> <th colspan="2">P2(4x-Pluggable-QSFP)</th> </tr> <tr> <th>PAD</th> <th>SIGNAL</th> <th>PAD</th> <th>SIGNAL</th> </tr> </thead> <tbody> <tr><td>02</td><td>TX2n</td><td>21</td><td>RX2n</td></tr> <tr><td>03</td><td>TX2p</td><td>22</td><td>RX2p</td></tr> <tr><td>05</td><td>TX4n</td><td>24</td><td>RX4n</td></tr> <tr><td>06</td><td>TX4p</td><td>25</td><td>RX4p</td></tr> <tr><td>14</td><td>RX3p</td><td>33</td><td>TX3p</td></tr> <tr><td>15</td><td>RX3n</td><td>34</td><td>TX3n</td></tr> <tr><td>17</td><td>RX1p</td><td>36</td><td>TX1p</td></tr> <tr><td>18</td><td>RX1n</td><td>37</td><td>TX1n</td></tr> <tr><td>21</td><td>RX2n</td><td>02</td><td>TX2n</td></tr> <tr><td>22</td><td>RX2p</td><td>03</td><td>TX2p</td></tr> <tr><td>24</td><td>RX4n</td><td>05</td><td>TX4n</td></tr> <tr><td>25</td><td>RX4p</td><td>06</td><td>TX4p</td></tr> <tr><td>33</td><td>TX3p</td><td>14</td><td>RX3p</td></tr> <tr><td>34</td><td>TX3n</td><td>15</td><td>RX3n</td></tr> <tr><td>36</td><td>TX1p</td><td>17</td><td>RX1p</td></tr> <tr><td>37</td><td>TX1n</td><td>18</td><td>RX1n</td></tr> <tr> <td>GND GROUP</td> <td>GND</td> <td>GND GROUP</td> <td>GND</td> </tr> <tr> <td>GND GROUP</td> <td></td> <td>GND GROUP</td> <td></td> </tr> <tr> <td>01,04,07,13,16,19</td> <td></td> <td>01,04,07,13,16,19</td> <td></td> </tr> <tr> <td>20,23,26,32,35,38</td> <td></td> <td>20,23,26,32,35,38</td> <td></td> </tr> <tr> <td>Connector Shell</td> <td></td> <td>Connector Shell</td> <td></td> </tr> </tbody> </table> <table border="1" style="width:100%; border-collapse: collapse;"> <thead> <tr> <th colspan="2">Low Speed Signal &amp; Power</th> </tr> <tr> <th>Pad</th> <th>SIGNAL</th> </tr> </thead> <tbody> <tr><td>08</td><td>ModSelL</td></tr> <tr><td>09</td><td>ResetL</td></tr> <tr><td>10</td><td>VccRx</td></tr> <tr><td>11</td><td>SCL</td></tr> <tr><td>12</td><td>SDA</td></tr> <tr><td>27</td><td>ModPrsL</td></tr> <tr><td>28</td><td>IntL</td></tr> <tr><td>29</td><td>VccTx</td></tr> <tr><td>30</td><td>Vcc1</td></tr> <tr><td>31</td><td>LPMODE</td></tr> </tbody> </table> <p>*DC BLOCKING CAPS ON P1,P2 RX END.</p>										HIGH SPEED SIGNAL				P1(4x-Pluggable-QSFP)		P2(4x-Pluggable-QSFP)		PAD	SIGNAL	PAD	SIGNAL	02	TX2n	21	RX2n	03	TX2p	22	RX2p	05	TX4n	24	RX4n	06	TX4p	25	RX4p	14	RX3p	33	TX3p	15	RX3n	34	TX3n	17	RX1p	36	TX1p	18	RX1n	37	TX1n	21	RX2n	02	TX2n	22	RX2p	03	TX2p	24	RX4n	05	TX4n	25	RX4p	06	TX4p	33	TX3p	14	RX3p	34	TX3n	15	RX3n	36	TX1p	17	RX1p	37	TX1n	18	RX1n	GND GROUP	GND	GND GROUP	GND	GND GROUP		GND GROUP		01,04,07,13,16,19		01,04,07,13,16,19		20,23,26,32,35,38		20,23,26,32,35,38		Connector Shell		Connector Shell		Low Speed Signal & Power		Pad	SIGNAL	08	ModSelL	09	ResetL	10	VccRx	11	SCL	12	SDA	27	ModPrsL	28	IntL	29	VccTx	30	Vcc1	31	LPMODE
HIGH SPEED SIGNAL																																																																																																																																	
P1(4x-Pluggable-QSFP)		P2(4x-Pluggable-QSFP)																																																																																																																															
PAD	SIGNAL	PAD	SIGNAL																																																																																																																														
02	TX2n	21	RX2n																																																																																																																														
03	TX2p	22	RX2p																																																																																																																														
05	TX4n	24	RX4n																																																																																																																														
06	TX4p	25	RX4p																																																																																																																														
14	RX3p	33	TX3p																																																																																																																														
15	RX3n	34	TX3n																																																																																																																														
17	RX1p	36	TX1p																																																																																																																														
18	RX1n	37	TX1n																																																																																																																														
21	RX2n	02	TX2n																																																																																																																														
22	RX2p	03	TX2p																																																																																																																														
24	RX4n	05	TX4n																																																																																																																														
25	RX4p	06	TX4p																																																																																																																														
33	TX3p	14	RX3p																																																																																																																														
34	TX3n	15	RX3n																																																																																																																														
36	TX1p	17	RX1p																																																																																																																														
37	TX1n	18	RX1n																																																																																																																														
GND GROUP	GND	GND GROUP	GND																																																																																																																														
GND GROUP		GND GROUP																																																																																																																															
01,04,07,13,16,19		01,04,07,13,16,19																																																																																																																															
20,23,26,32,35,38		20,23,26,32,35,38																																																																																																																															
Connector Shell		Connector Shell																																																																																																																															
Low Speed Signal & Power																																																																																																																																	
Pad	SIGNAL																																																																																																																																
08	ModSelL																																																																																																																																
09	ResetL																																																																																																																																
10	VccRx																																																																																																																																
11	SCL																																																																																																																																
12	SDA																																																																																																																																
27	ModPrsL																																																																																																																																
28	IntL																																																																																																																																
29	VccTx																																																																																																																																
30	Vcc1																																																																																																																																
31	LPMODE																																																																																																																																
DESC. QSFP FDR 14G Cable Assembly				APPROVED	CHECKED	DESIGNED	TOLERANCE	SCALE	#	UNIT	mm																																																																																																																						
P/N UA55-RC005982 CUSTOMER P/N						Sino		DATE	01/23/13	DWG NO.:	DWG\RC\5982																																																																																																																						