



PA AMPLIFIER

1, FRONT PANEL INFORMATION



- (1) POWER: ON/OFF
- (2) USB/SD/FM, MP3 PLAYER DISPLAY UNIT
- (3) FIVE ZONES
- (4) INDICATOR LIGHT: ERROR, POWER AND SIGNAL
- (5) MASTER VOLUME CONTROL
- (6) TREBLE & BASS
- (7) AUX INPUT VOLUME CONTROL
- (8) MP3 VOLUME CONTROL
- (9) MIC VOLUME CONTROL
- (10) MIC INPUT, MIC1 WITH MUTE PRIORITY

2, BACK PANEL INFORMATION



- (1) AUX OUTPUT
- (2) AUX INPUT
- (3) 4-16 Ohm OUTPUT
- (4) 70V OUTPUT
- (5) NO. 5 ZONE
- (6) NO. 4 ZONE
- (7) NO. 3 ZONE
- (8) NO. 2 ZONE
- (9) NO. 1 ZONE
- (10) POWER SUPPLY AC220V
- (11) FUSE
- (12) ANTENNA
- (13) COM

3, TECHNICAL FEATURES

- 1). POWER OUTPUT: MP3-60U 60W
MP3-100U 100W, MP3-150U 150W
- 2) OUTPUT: 4-16 Ohm/70V/100V
- 3) Frequency response : 40Hz-18KHz ± 0.5 dB
- 4) Total Harmonic Distortion: <0.2%(RMS)
- 5) Power Voltage: AC220V 50-60Hz
- 6) SIZE: 482*300*66MM

4, NOTE

- 1) AC220 (50Hz-60Hz)
- 2) Don't Put the Vents to Avoid Emission Effect.
- 3) To Avoid Unnecessary Load Circuit.
- 4) When Play MP3, If Mic and Circuit are Not Used, Please Put Off the Knob.
- 5) When the Machine is Abnormal, Non-professional Persons Do not Open and Maintain It, to Avoid Electric Shock Accidents.

BUY ON
www.cablematic.com