

Features

Voltage: AC100-240V 50Hz/60Hz

Power: 20W

Light source:300pcs 10mm LEDs(60R,60G,60B,60A,60W)

4operation modes: Automatic running, DMX, Sound Active, Master/Slave

Sound controlled via built-in microphone

7 DMX channels

4-button LED DMX display

Advantages of LED-technology: extremely long life, low power consumption minimal heat emission, defacto maintenance free with brilliant light radiation

Package size:82*20*19.5CM

Weight:4kg

BUY ON

www.cablematic.com

1,Digital display

Addr, A001-A512 DMX

SLAU, slave mode

AUTO, auto run

Soud, sound active

2,DMX operation

CH1	0-255	Different effect auto run
CH2	0-85	Red 1
	86-170	Red 2
	171-255	Red 1&Red 2
CH3	0-85	Green 1
	86-170	Green 2

	171-255	Green 1& Green 2
CH4	0-85	Blue 1
	86-170	Blue 2
	171-255	Blue 1& Blue 2
CH5	0-85	Amber 1
	86-170	Amber 2
	171-255	Amber 1& Amber 2
CH6	0-85	white 1
	86-170	white 2
	171-255	white 1& white 2
CH7	0-255	Dimmer, bright to dark...blackout

Safety instruction

CAUTION!

Be careful with your operations. With a dangerous voltage you can suffer a dangerous electric shock when touching the wires!

Electric shock when touching the wires!

This device has left our premises in absolutely perfect condition. In order to maintain this condition and to ensure a safe operation, it is absolutely necessary for the user to follow the safety instructions and warning notes written in this manual.

Please note: Every information is subject to change without prior notice