

VeraSol Standardized Specifications Book

Manufacturer: Omnivoltaic Energy Solutions Co. Ltd

Component Family Name: LUMN HOME Family

**Date of Specifications Book
Expiration:** April 30, 2025

Verify Online: www.verasol.org/products/omni-homefam

Contact Information: sales@omnivoltaic.com

Website: www.omnivoltaic.com



This VeraSol Standardized Specifications Book presents a **component-level Standardized Specifications Sheet** listing the available components in the product family by component type, each individual component's performance rating, and performance results for each component tested according to the Edition 4 of IEC 62257-9-5. Following the component-level Standardized Specifications Sheet is a **list of the systems** covered by this Specifications Book that use combinations of these components.

NOTICE: Systems or kits developed using components from the component family will each perform differently and have not all been evaluated on a system-level basis. All systems listed in this Specifications Book are regarded to have passed IEC TS 62257-9-8.

Quality Standards Framework Version: 2023

Revision: 2023.06

Component-Level Standardized Specifications Sheet

Omnivoltaic Energy Solutions Co. Ltd

LUMN HOME Family

Battery / Control Box

Name / Model Number	Battery Chemistry	Nominal Voltage (V)	Battery Capacity Rating (Ah)	Measured Battery Capacity (Ah)
SHS 20	Lithium iron phosphate	3.3	6	6
SHS 40	Lithium iron phosphate	3.3	12	12
Torch battery	Lithium iron phosphate	3.2	0.63	0.63

PV Module

Name / Model Number	Peak Power at STC Rating (W)	Measured Peak Power at STC (W)
6 W PV module	6	6
12 W PV module	12	12

Light Sources*

Name / Model Number	Luminous Flux Rating (lm)	Measured Luminous Flux (lm)	Measured Lamp Efficacy (lm/W)
	high	high	high
LED lamp	210	190	190
Security Lamp	200	190	170
LED tubelight	410	350	170
Torch- Side Light	40	46	140
Torch-Front Light	33	Not Tested	Not Tested

Appliances*

Name / Model Number	Description	Rated Power (W)	Measured Power During Use (W)	Rated Battery Capacity (mAh)	Measured Battery Capacity (mAh)
Solar Powered Radio	Portable Radio with 3.7 V internal battery, charges via USB	3	0.39	1	1.1

*Light points and appliances may perform differently when used with different systems.

NOTICE: As indicated, not all components listed on this page were tested according to the Quality Test Method (QTM) in Edition 4 of IEC 62257-9-5. However, based on the satisfactory performance of the tested components in the family, the components that were not tested are regarded to have passed IEC TS 62257-9-8:2020. In addition, all tested components passed an internal inspection, the full array of applicable QTM durability tests, as well as ingress protection testing (where applicable).

List of Covered Systems

Omnivoltaic Energy Solutions Co. Ltd
LUMN HOME Family

System Name	Number of each component included in each system								
	LED Lamp (L2)	Security Lamp (S2)	Tubelight (T4)	6 W PV module	12 W PV module	SHS 20 control unit (6 Ah battery)	SHS 40 control unit (12 Ah battery)	Torch (X)	Radio (RD)
SHS20_06W_T4_L2	1	--	1	1	--	1	--	--	--
SHS20_06W_L22	2	--	--	1	--	1	--	--	--
SHS20_06W_L22_S2	2	1	--	1	--	1	--	--	--
SHS20_06W_L222	3	--	--	1	--	1	--	--	--
SHS20_06W_L222_S2	3	1	--	1	--	1	--	--	--
SHS20X_06W_L22	2	--	--	1	--	1	--	1	--
SHS20X_06W_L22_S2	2	1	--	1	--	1	--	1	--
SHS20X_06W_L222_RD	3	--	--	1	--	1	--	1	1
SHS40_12W_L2222	4	--	--	--	1	--	1	--	--
SHS40_12W_T444	--	--	3	--	1	--	1	--	--
SHS40_12W_T444_S2	--	1	3	--	1	--	1	--	--
SHS40_12W_T4_L222	3	--	1	--	1	--	1	--	--
SHS40_12W_L22_S2	2	1	--	--	1	--	1	--	--
SHS40_12W_L222_S2	3	1	--	--	1	--	1	--	--
SHS40_12W_T4_L2_S2 **	1	1	1	--	1	--	1	--	--
SHS40_12W_T4_L22_S2	2	1	1	--	1	--	1	--	--
SHS40X_12W_L22_S2	2	1	--	--	1	--	1	1	--
SHS40X_12W_T4_L22_S2_RD	2	1	1	--	1	--	1	1	1
SHS40X_12W_L2222_RD	4	--	--	--	1	--	1	1	1
SHS40X_12W_T444_S2_RD	--	1	3	--	1	--	1	1	1
SHS40X_12W_T4_L22_S2_RD	2	1	1	--	1	--	1	1	1

**Tested as full systems. Individual SSS available on VeraSol website.

These SKUs are interpreted as follows In: SHSyX_ZZ_Txxxx_Lxxxx_Sxxxx_P

- yX: y-can be either 20 or 40, and is used to represent different battery capacity of 6Ah(20Wh),12Ah(40Wh) respectively,

X-is used to represent a torch is included in the kit or blank.

-ZZ: can be either 06W or 12W, and is used to represent different PV module sizes of 6W and 12W respectively.

-Txxxx: each x can be either 4 or blank, and is used to represent the type and number of LED tube (410lumen) included with the kit. For example, LT4444 includes four 410-lumen LED tubes.

-Lxxxx: each x can be either 2 or blank, and is used to represent the type and number of LED lamp (210lumen) included with the kit. For example, L2222 includes four 210-lumen LED lamps.

-Sxxxx: each x can be either 2 or blank, and is used to represent the type and number of Security light (200lumen) included with the kit. For example, S2222 includes four 200-lumen security lights

-P: can either be VeraSol certified products like RD (radio) or blank.

NOTICE:

Only the kits denoted with ** were tested as full systems according to Edition 4 of IEC 62257-9-5 and passed IEC 62257-9-8 standards. An Individual Standardized Specification Sheet (SSS) that reports system-level performance is available for these systems at VeraSol.org. Systems that were not tested, but that were developed using components from the component family will perform differently than the system(s) shown in the individual system-level SSS. All systems listed above are regarded to have passed IEC 62257-9-8.

Unless otherwise noted, the following information applies to all listed systems and components:

Warranty Information

A 2-year warranty covering manufacturing defects in the system and a 1-year warranty for appliances and USB charging cable

Available Daily Electrical Energy and Port Information

Omnivoltaic Energy Solutions Co. Ltd
LUMN HOME Family

System Name	Available Daily Electrical Energy (Wh/day)	Includes ports for charging?
SHS20_06W_L22	15	yes
SHS40_12W_T444	33	yes
SHS40_12W_L222_S2	33	yes
SHS40_12W_T4_L2_S2**	33	yes

**Tested as full system. Individual SSS available on VeraSol website.

NOTICE:

The available daily electrical energy (Wh/day) is calculated for fully tested systems following the energy service calculations as described in IEC/TS 62257-9-5 Ed. 4. For products in a family that are not tested as a full system, estimations of available daily electrical energy (Wh/day) are calculated according to an alternative method using data from the test reports of fully-tested products and components.