Santa Technology Company Limited (Headquarters)

Santatechnology.com

santatech@gmail.com 02-101-3454 02-101-3453 (Fax.) 089-006-2766 @santatech

XINTEST HT-430 Light meter

Features

Auto revise parameters and measurement

User selectable Lux/Fc

MAX/MIN record

Low battery indication

Auto power off

Specifications

light lux meter from 0.1 Lux to 400,000 Lux and 0.01FC to 40,000FC

Special function	Auto power off with disable feature;Data hold; MAX MIN; Back light
Accuracy	±(3% +30 digits) to reference
Sample rate	1 time/sec
Auto power off	about 15 minutes idle
Operating environment	0~+50°C(32~+122°F), 0~85%RH
Storage environment	-20~+60°C(-4~+140°F), 0~85%RH
Power Supply	DC1.5V (AAA) x 2pcs(included)
Dimension	170 X 55 X 33mm
Weight	about 187g