

Current Calibrator

multicomp

RoHS
Compliant



Features

- Provides quality and accuracy of handheld calibrator of precision current source
- Adjustable 0-24mA current source, 2 ranges
- Portable instrument for calibrating process devices and measuring process signals
- Current calibrator drives loads up to 500Ω

www.element14.com
www.farnell.com
www.newark.com

multicomp

Current Calibrator



Specifications

Display	: LCD Display Max. Display Counts 1999 13mm (0.5") Digit Size
Function	: mA Current Source, 2 Ranges.
Sampling Time	: Approx. 0.4 second
Operating Temperature	: 0°C to 50°C (32°F to 122°F)
Operating Humidity	: Less than 80% RH
Power Supply	: 006P DC 9V, MN1604/PP3 Battery or Equivalent Alkaline type or Heavy Duty
Dimension	: 185mm × 78mm × 38mm (7.3" × 3" × 1.5")
Weight	: 265g/0.58lb. (Including battery)

Electrical Specifications

Range	Display Resolution	Accuracy
0 - 19.99mA	0.01mA	±(0.25% FS* + 1digit)
0 - 24mA	0.1mA	±(0.5% FS* + 1digit)

*FS: Full Scale

Part Number Table

Description	Part Number
Current Calibrator	72-6694

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp is the registered trademark of the Group. © Premier Farnell Limited 2016.

www.element14.com
www.farnell.com
www.newark.com

