



SUBMINIATURE POWER RELAY



Features

- Slim size (width 5mm)
- High breakdowm voltage 4kV (between coil and contacts)
- Surge voltage up to 6kV (between coil and contacts)
- Clearance/creepage distance: 8mm
- High sensitive: 170mW
- Sockets available
- 1 Form A and 1 Form C configurations
- Environmental friendly product (RoHS compliant)
- Outline Dimensions: (28.0 x 5.0 x 15.0) mm

CO	NTA	CT	DA.	ГΑ

File No.:40020043

Contact arrangement	1A, 1C
Contact resistance	100m Ω (at 1A 6VDC) Gold plated: 30m Ω (at 1A 6VDC)
Contact material	AgNi, AgSnO ₂
Contact rating (Res. load)	6A 250VAC/30VDC
Max. switching voltage	400VAC / 125VDC
Max. switching current	6A
Max. switching power	1500VA / 180W
Mechanical endurance	1 x10 ⁷ ops
	1A: 6x10⁴ ops (at 85°C)
Electrical endurance	1C: (NO) 3x10⁴ ops (at 85°C) (NC) 1x10⁴ ops (at 85°C)

		\sim TCD	ICT	
CHA	KA	CTER	1211	Lo

Insulation resistance			1000MΩ (at 500VDC)
Dielectric Between		coil & contacts	4000VAC 1 min
strength	Between open contacts		1000VAC 1 min
Operate time (at nomi.volt.)			8ms max.
Release time (at nomi.volt.)			4ms max.
Shock resistance		Functional	50m/s² (5g)
		Destructive	1000m/s² (100g)
Vibration resistance			10Hz to 55Hz 1mm DA
Humidity			5% to 85% RH
Ambient temperature			-40°C to 85°C
Termination			PCB
Unit weight			Approx. 5.4g
Construction			Wash tight, Flux proofed

Notes:

- 1) The data shown above are initial values.
- 2) Please find coil temperature curve in the characteristic curves below.
- 3) When install 1 Form C type of HF41F, please do not make the relay side with 5mm width down.

COIL	
Coil power	5 to 24VDC: 170mW
	48VDC, 60VDC: 210mW

COIL DATA				at 23°C
Nominal Voltage VDC	Pick-up Voltage VDC	Drop-out Voltage VDC	Max. Allowable Voltage VDC	Coil Resistance Ω
5	3.75	0.25	7.5	147 x (1±10%)
6	4.50	0.30	9.0	212 x (1±10%)
9	6.75	0.45	13.5	476 x (1±10%)
12	9.00	0.60	18	848 x (1±10%)
18	13.5	0.90	27	1906 x (1±15%)
24	18.0	1.20	36	3390 x (1±15%)
48	36.0	2.40	72	10600 x (1±15%)
60	45.0	3.00	90	16600 x (1±15%)

Notes: When require pick-up voltage=70% nominal voltage, special order allowed .

UL&CUR Resistive: 6A 277VAC Pilot duty: R300 B300

SAFETY APPROVAL RATINGS

VDE (AaNi)	6A 30VDC
VDE (AgNi)	6A 250VAC

Notes: Only some typical ratings are listed above. If more details are required, please contact us.





ENGLISH


OUTLINE DIMENSIONS, WIRING DIAGRAM AND PC BOARD LAYOUT

Unit: mm


Outline Dimensions









1 Form C



Flat pack version







ENGLISH

Unit: mm


OUTLINE DIMENSIONS, WIRING DIAGRAM AND PC BOARD LAYOUT PCB Layout


1 Form A

(Bottom view)


1 Form C


Vertical version






Flat pack version





Wiring Diagram (Bottom view)

1 Form A





Remark: 1) In case of no tolerance shown in outline dimension: outline dimension ≤1mm, tolerance should be ±0.2mm; outline dimension >1mm and ≤5mm, tolerance should be ±0.3mm; outline dimension >5mm, tolerance should be ±0.4mm.


2) The tolerance without indicating for PCB layouts is always ±0.1mm.

CHARACTERISTIC CURVES

MAXIMUM SWITCHING POWER







Percentage Of Nominal Coil Voltage

Disclaimer

This datasheet is for the customers' reference. All the specifications are subject to change without notice.

We could not evaluate all the performance and all the parameters for every possible application. Thus the user should be in a right position to choose the suitable product for their own application. If there is any query, please contact Hongfa for the technical service. However, it is the user's responsibility to determine which product should be used only.