

## FEATURES

- Impedance of 75 ohms
- Nickel plated body
- Operating frequency of 250 MHz
- Stock number 7902805 is a BNC plug to RCA jack adapter
- Stock number 7902809 is an RCA plug to BNC jack adapter

## Straight 75Ω RF Adapter RCA Plug to BNC Socket 250MHz

RS Stock No.: 790-2809



RS Professionally Approved Products bring to you professional quality parts across all product categories. Our product range has been tested by engineers and provides a comparable quality to the leading brands without paying a premium price.

## Product Description

From RS PRO comes a range of high quality and great value coaxial adapters, These coaxial type adapters have been designed to provide an effective method of connecting coaxial cable assemblies through a panel mounting connection. Manufactured out of industry standard components, these connectors are most commonly used for connecting radio and television broadcast equipment.

## General Specifications

<b>Adapter Type</b>	RCA Plug to BNC Socket
<b>Adapter Type A</b>	RCA
<b>Adapter Type B</b>	BNC
<b>Gender A</b>	Male
<b>Gender B</b>	Female
<b>Body Orientation</b>	Straight
<b>Contact Plating</b>	Gold
<b>Body Plating</b>	Nickel
<b>Contact Material</b>	Brass
<b>Insulation Material</b>	POM
<b>Body Material</b>	Brass
<b>Washer Material</b>	Brass
<b>Centre contact Material</b>	Brass
<b>Body Finish</b>	Nickel 100µ" min
<b>Washer Finish</b>	Nickel
<b>Centre Contact Finish</b>	Gold
<b>Application</b>	Test and measurement, Communication systems, GPS equipment, Antennas, Wi-Fi equipment

## Electrical Specifications

Impedance	75 $\Omega$
Operating Frequency	250MHz

## Mechanical Specifications

Length	30.5 mm
--------	---------

## Operation Environment Specifications

Operating Temperature	-40 to +65°C
-----------------------	--------------

## Approvals

Compliance/Certifications	2011/65/EU and 2015/863
---------------------------	-------------------------



Dimensions: (mm)

