# Switch **Emergency Stop**

# multicomp PRO




# **Specifications:**

Bounce Time

External Depth	: 49.2mm
External Diameter	: 24mm
Lead Spacing	: 2.5mm
Panel Cutout Diameter	: 16mm
Panel Thickness Max.	: 5mm
Terminal Type	: PCB Pins
<b>Electrical:</b> Maximum Switching Power Maximum Switching Voltage Maximum Switching Current Dielectric Strength (50Hz/1 Minute)	: 30V DC : 32V DC : 100mA DC : 750V between open contacts
<b>Operting Life:</b>	: ≥1 × 10 <sup>5</sup> operations
OA (Momentary)	: ≥1 × 10 <sup>5</sup> operations
EE (Push-Push)	: Initial ≥100mΩ; 50mΩ
Contact Resistance	: Afer life 150mΩ
Insulation Resistance	: ≥10 <sup>10</sup> Ω


: ≤3ms

#### **Plug-in Emergency Stop Switch**



#### **Dimensions : Millimetres**

## **Hole Diameter**



### Part Number Table

Description	Part Number
Emergency Stop Switch - AC Switching	MCOS38009

Important Notice : This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro

