Keylock Switches

multicomp PRO



Features

RoHS Compliant

- NS106-1, NS106-2 and NS106-M
- · Zinc alloy keys, chrome plated with plastic cover
- · Silver plated contacts and terminals
- · 4 pins tumbler mechanism
- NS106 2 Positions (off-on) 2 terminals
- NS106 2 Positions (off-on) 4 terminals
- NS106M 2 Positions (off-on) 2 spring loaded for momentary contact

Specifications

Contact Rating : 1A at 125V AC, 0.5A at 250V AC

Max. Contact Resistance : $10m\Omega$

 $\begin{array}{ll} \mbox{Insulation Resistance} & : 200 \mbox{M}\Omega \mbox{ minute (500V DC)} \\ \mbox{Dielectric Strength} & : 1,000 \mbox{ AC at 1 minute} \end{array}$

Combinations : 200

Housing : Zinc alloy die cast, chrome plated

Key-Pull Figures

- o Off Position
- Indicates Key-Pull
- Indicates No Key-Pull









Figure 1


Figure 2 Figure 3

3 Figure 4

Figure Number	Lock Number	Pole	Positions	Terminals	Key Pulls	Lum	1	J	Туре
1	NS106-1				1				
2	NS106-2	1	2	2	2	90	Off	On	SPSI
1	NS106M				1				

Diagram

NS106-1, NS106-2 and NS106-M



Dimensions: Millimetres

Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro



Keylock Switches




S116-1

Features

- · Zinc alloy die cast housing and cylinder, chrome plated
- · Zinc alloy keys, chrome plated.
- · Silver plated contacts and terminals
- 2 positions (on-on) 4 terminals
- · 150 Combinations available
- · Rating: 1A at 125V AC, 0.5A at 250V AC

Diagram




S116-2

Features

- · Zinc alloy die cast housing and cylinder, chrome plated
- · Zinc alloy keys, chrome plated
- · Silver plated contacts and terminals
- 2 positions (on-on) 4 terminals
- A O'clock position (1-3 on)
- B O'clock position (2-4 on)
- · 150 combinations available
- Rating: 1A at 125V AC, 0.5 A at 250V AC

Diagram



Dimensions : Millimetres

Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro



Keylock Switches



Part Number Table

Description	Part Number		
Keyswitch, SPST, 2 Pos, RDM, 1 Keypull	NS106-1		
Keyswitch, SPST, 2 Pos, RDM, 2 Keypull	NS106-2		
Keyswitch, SPDT, 2 Pos, RDM, 1 Keypull	S116-1		
Keyswitch, SPDT, 2 Pos, RDM, 2 Keypull	S116-2		
Keyswitch, SPST, 2 Pos , MOM, RDM	NS106-M		

Important Notice: This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro

