

RoHS Compliant

# **Specifications**

Dice material : AlGalnP
Emmiting Colour : Green
Lens colour : Water clear
Viewing angle : 140°
Dominant Wavelength :576nm
Luminous Intensity :80mcd

## Absolute Maximum Ratings at Ta=25°C

Parameter	Symbol	Rating	Unit	
Power Dissipation	PD	85	mW	
Forward current	lf	25	mA	
Reverse Voltage	Vr	5	V	
Peak Pulsing Current	lfp	100	mA	
Operating Temperature	Тор	-40 to +85	°C	
Storage Temperature	Tstg.	-40 to +100	°C	
Peak Current (1/10Duty Cycle,0.1ms Pulse Width.)	If (peak)	100	mA	
Lead Soldering Temperature. (1.6mm from seating plane)	Tsol.	Reflow Soldering : 260°C for 3 sec. Hand Soldering: 350°C for 3 sec.		
Electrostatic Discharge	ESD	2000 V		

## **Electrical and Optical Characteristics**

Parameter	Symbol	Condition	Min.	Тур.	Max.	Unit
Luminous Intensity	lv	If=20mA	32		80	mcd
Forward Voltage	Vf	If=20mA	1.8		2.4	V
Dominant Wavelength	λd	If=20mA	566		576	nm
Reverse Current	lr	Vr=5V				μΑ
Viewing Angle	201/2	If=20mA		140		deg
Spectrum Line Halfwidth	Δλ	If=20mA		15		nm

#### Notes


- 1. Tolerance of Luminous Intensity is ±15%
- 2. Tolerance of Forward Voltage is ±0.1V
- 3. Tolerance of Dominant Wavelength is ±1nm


Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro








Typical Electrical/Optical Characteristic Curves (25°C Ambient Temperature Unless Otherwise Noted)












Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro





#### **Dimensions**



Tolerance is ±0.1mm unless otherwise noted.

Dimensions: Millimetres

### Precautions in use:

#### Storage

It is recommended to store the products in the following conditions:

- 1. Do not open the moisture proof bag before ready to use the LEDs
- 2. The LEDs should be kept at 30°C or less and 60%RH or less before opening the package. The max. storage period before opening the package is 1 year.
- 3. After opening the package, the LEDs should be kept at 30°C/40%RH or less, and it should be used within 7 days
- If the LEDs are stored contrary to 3, baking is required before mounting. Baking condition: 60 ±5°C for 24 hours

## **Hand Soldering**

The temperature of the iron should be lower than 300oC and soldering within 3sec per solder-pad is to be observed. Avoid using organic solvent.

Recommend ultrasonic method 300W Max.


### Cleaning

Surface condition of this device may change when organic solvents such as trichloroethylene or acetone were applied.





## **Reflow Temp/Time**



### Notes:

- 1. Reflow soldering should not be done more than two times.
- 2. Do not put stress on the LEDs when soldering.
- 3. Do not warp the circuit board before it have been returned to normal ambient conditions after soldering.

## **Reflow Soldering Pad Dimensions**



## **Part Number Table**

Description	Part Number	
Chip LED, Green, 576nm, 140°, 80mcd, Surface Mount	MP008255	

Important Notice: This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro

