

Datasheet

RS Pro Right Angle 50Ω RF Adapter SMT Plug to FME Plug 6GHz

RS Stock No: **738-5923**



Product Details

RS Pro right angle RF adapter has SMT plug and FME plug connecting ends that operates at a frequency of 6 GHz. The RF adapter measuring 110 mm, works at a nominal impedance of 50 Ω.

Features and Benefits

- Nominal impedance of 50Ω
- Frequency of 6 GHz
- 110 mm long

**Specifications:**

Adapter Type A	SMT
Adapter Type B	FME
Adapter Type	SMT Plug to FME Plug
Body Orientation	Right Angle
Contact Material	Brass
Gender A	Plug
Gender B	Plug
Impedance	50 Ω
Length	110 mm
Operating Frequency	6 GHz
Body Material	Brass
Insulation Material	PTFE
Operating Temperature	-40 to +90°C
Voltage Rating	100 V