

DOCTOR-START330



- Battery manager for complete maintenance and rapid cranking of 12V/24V Wet, Gel, AGM, MF, PbCa, EFB and Li batteries. 300A start max. With LCD screen
- Automatic charging and trickle charging in Pulse Tronic based on the technology of the selected battery
- Battery test, cranking and alternator, regeneration and recovery of batteries; source of stable power supply for battery changes; cranking

Description

Multifunction, electronic battery charger, starter and tester (BATTERY MANAGER), for WET, GEL, AGM, MF, PbCa, EFB and Li batteries at 12V/24V.

It grants complete maintenance of the batteries and quick starting of cars, vans and light trucks.

It is an indispensable tool for stable power supply during battery changes.

Easy and intuitive to use thanks to the graphical LCD screen.

Technical Data

Single Phase Mains Voltage	230 V
Mains frequency	50/ 60Hz
Charge power	1 kW
Start power	6.4 kW
Charging voltage	12/ 24V
Effective charging current	45 A
Rated charge curr. EN60335-2-29	31 A
Start current 1V/C EN60335-2-29	180 A
Max. starting current	300 A
Min. rated reference capacity	10 Ah
Max. rated reference capacity	450 Ah
Dimensions	30.5 x 36 x 63 cm
Weight	12.5 kg