## Short Metal Pushbutton Switches **Multicomp** PRO

## RoHS Compliant



### **Specifications**

Rating	: 2A/36V DC	
Electrical Life	: 200,000 make-and-break cycles at full load.	
Mechanical Life	: 1,000,000. Cycles	
Dielectric Strength	: 2,000V RMS@sea level	
Contact Resistance	: 50m $\Omega$ MAX. @1A 12V DC (initial value)	
Operating Temperature	: -20°C to 70°C	
Travel	: ABOUT 1.8 ±0.2mm	
Operation Pressure	: 4.5 ±1.5N	
Ingress Protection	: IP67, IK10 (Stainless)	
Torque	: 1Nm to 3Nm	
Current limiting resistor is required to limit led forward current to 20mA		


### **Materials**

Bushing	: Stainless Steel	
Base	: PA66, White UL-94V0	
Actuator	: PC, Translucent UL-94V2 Stainless Steel	
Inner Assembly : PC, Transparent UL-94V2		
Spring	: Spring steel	
Sealing	: Sillicone, Translucent	
O-Ring	: Sillicone, Black	
Terminal	: Brass, Gold flash plated	
Contact	: Brass, Sliver alloy	
Hex Nut	: Brass, Nickel plated	


Newark.com/multicomp-pro Farnell.com/multicomp-pro sg.element14.com/b/multicomp-pro

# multicomp PRO


## Short Metal Pushbutton Switches **Multicomp** PRO



## Body Type




#### Panel Cutout Thickness: 6.0mm(Max.)




Newark.com/multicomp-pro Farnell.com/multicomp-pro sg.element14.com/b/multicomp-pro




## Short Metal Pushbutton Switches **Multicomp** PRO






E Ring



#### P Power+Ring



**Dimensions : Millimetres** 

Newark.com/multicomp-pro Farnell.com/multicomp-pro sg.element14.com/b/multicomp-pro



### Part Number Table

Description	Part Number
Pushbutton Switch, 25mm, Red LED	MPM25-A02FE-3-JR-3V
Pushbutton Switch, 25mm, Red LED	MPM25-A01FP-3-JR-3V

Important Notice : This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/multicomp-pro Farnell.com/multicomp-pro sg.element14.com/b/multicomp-pro

