Digital Panel Display



RoHS Compliant

Description

MP-335PAS is a 4-digit pasive analog loop display 4 to 20mA. The instrument is based on a microcontroller with a very low power consumption and an A/D converter, which ensures good accuracy and easy mounting into mosaic and signaling panels. operation of the instrument.

The 22 mm cross-section of the circular instrument body allows its convenient mounting into mosaic and signaling panels.

Features

- · 4-Digit Programmable Projection
- Input: 4mA to 20mA
- Linearization
- Size of DIN 51.5mm × 29.5mm
- · Power Supply From The Loop

Specification

Projection

Display : 9999, 7-segment LED

Digit height : 14 mm

Display color : Red or Green

Projection : -999 to 9999

Decimal point : Adjustable - in menu

Brightness : Fixed

Instrument Accuracy

TK : 50 ppm/°C

Accuracy : ±0.15% of range + 1 digit (for projection -999 to 1999)

Rate : 0.1 to 100 measur./s

Overload capacity : 2x

Watch-dog : Reset after 500 ms
Calibration : At 25°C and 40 % r.h.

Newark.com/multicomp-pro Farnell.com/multicomp-pro sg.element14.com/b/multicomp-pro



Digital Panel Display



Comparators

Type : Digital, menu adjustable

Hysteresis mode : Switching limit, hysteresis band "Lim ±1/2Hys." and time (±99.9 s) determining the switching delay

Output : 2x Power MOSFET, (30V DC/0.5 A)

Power Supply

from current loop 4 to 20mA, voltage drop < 6 V

Mechanic Properties

Material : Noryl, incombustible UL 94 V-1 Dimensions : $51.5 \times 29.5 \times 66$ mm (w × h × d)

Panel cutout : Ø 22.5mm

Operating Conditions

Connection : Connector terminal blocks, section 0.2mm² to 1.3mm²


Stabilization period : Within 2 minutes after switch-on

Working temperature : -20°C to 60°C Storage temperature : -20°C to 85°C

Protection : IP65 (front panel only)

EMC : EN 61326-1

Diagram



Part Number Table

Description	Part Number
4 Digit Process Monitor/Controller, 4-20mA, Red	MP-335PAS-1
4-digit Process Monitor/Controller, 4-20mA, Green	MP-335PAS-2

Important Notice: This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/multicomp-pro Farnell.com/multicomp-pro sg.element14.com/b/multicomp-pro

