

ALPINE 20 BOOST



Product may differ from Image

- Battery charger for WET 12/24V batteries. With ammeter and normal or fast (BOOST) charge selector. 300W.
- Protection against overcharging and pole inversion.

Description

Battery charger for charging free electrolyte batteries (WET) with 12V/24V voltage. Protected against overloads and polarity reversal. Equipped with selector for normal or quick (BOOST) charge. Equipped with ammeter.

Technical data

Single Phase Mains Voltage	230 V
Mains frequency	50/ 60Hz
Charging Absorbed Power	300 W
Charging voltage	12/ 24V
Effective charging current	18/ 12 A
Rated charge curr. EN60335-2-29	12/ 8 A
Min. rated reference capacity	30/ 20 Ah
Max. rated reference capacity	225/ 180 Ah
Adjustment positions	2
Dimensions	22.5 x 29 x 20.5 cm
Weight	6.9 kg