Bridge Rectifier Diode



RoHS

Compliant



Features

- Glass passivated
- · High surge forward current capability
- Reliable low cost construction utilizing moulded plastic technique results in expensive product
- · Lead tin plated copper
- · Mounting position: Any
- · Lead free

Applications

General purpose use in AC/DC bridge full wave rectification, for SMPS, lighting ballast, adapter, etc.


Max. Ratings and Electrical Characteristics


Rating at 25°C ambient temperature unless otherwise specified. Single phase, half wave, 60Hz, resistive or inductive load. For capacitive load, derate current by 20%.


| Characteristics | Symbol | Values | Unit |
|--|------------------|-------------|------------------|
| Max. Recurrent Peak Reverse Voltage | VRRM | 1,000 | |
| Max. RMS Bridge Input Voltage | VRMS | 700 | V |
| Max. DC Blocking Voltage | VDC | 1,000 | |
| Max. Average Forward Rectified Current at TA = 25°C | I(AV) | 2 | _ |
| Peak Forward Surge Current, 8.3ms Single Half Sine-wave Super Imposed on Rated Load (JEDEC Method) | IFSM | 60 | A |
| I ² t Rating for Fusing (t < 8.3 ms) | l ² t | 15 | A ² s |
| Peak Forward Voltage per Diode at 2A DC | VF | 1.1 | V |
| Maximum DC Reverse Current at Rated T _J = 25°C DC Blocking Voltage per Diode T _J = 100°C | lR | 10 1 | μA mA |
| Typical Junction Capacitance (Note 1) | Cı | 30 | pF |
| Operating Junction Temperature Range | TJ | -55 to +150 | °C |
| Storage Temperature Range | Тѕтс | | |

Note:

Rating and Characteristics Curves







Newark.com/multicomp-pro Farnell.com/multicomp-pro sg.element14.com/b/multicomp-pro





25/07/22 V1.1

^{1.} Measured at 1MHz and applied reverse Voltage of 4V DC

Bridge Rectifier Diode







Diagram

.181 (4.6) .150 (3.8) .183 (27.5) Min POS. .028 (0.71) LEAD .220 (5.6) .180 (4.6) .180 (4.6)

Part Number Table

| | Description | Part Number | |
|---|---|-------------|--|
| ĺ | Bridge Rectifier Diode, Single Phase, 1kV, 2A | 2W10MG | |

Dimensions: Inches (Millimetres)

Important Notice: This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/multicomp-pro Farnell.com/multicomp-pro sg.element14.com/b/multicomp-pro

