Connector DC Power Jack, 5A



RoHS Compliant



Specifications:

Electrical

 $\begin{array}{lll} \mbox{Connector Type} & : \mbox{DC Power} \\ \mbox{Contact Rating} & : \mbox{5A at 16V DC} \\ \mbox{Contact Resistance} & : \mbox{30m} \mbox{\Omega Max}. \end{array}$

 $\begin{array}{ll} \mbox{Insulation Resistance} & : 50 \mbox{M} \mbox{Min. at } 500 \mbox{V DC} \\ \mbox{Dielectric Strength} & : 500 \mbox{V AC for 1 minute} \end{array}$

Mechanical

Life Cycle : 5,000 Cycles
Insertion Force : 0.3kg to 3kg
Withdrawal Force : 0.3kg to 3kg


Environmental

Operating Temperature : -25°C to +70°C

Part Shall withstand Wave Solder Temperature of 260°C for 5 seconds

Schematic	'X'=DWG. No.	Pin Diameter
O 1) Pin Terminal O 2) Sleeve Shunt O 3) Sleeve Spring	-1	1.45 +0.0 / -0.1
	-2	1.87 +0.0/ -0.1
	-3	2 +0.0/-0.1
	-4	2.35 +0.0/-0.1
	-5	2.5 +0.0/-0.1

Diagram



PCB Layout Bottom View

Dimensions: Millimetres


Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro





19/02/21 V1.0

Connector DC Power Jack, 5A









Item	Description	Qty	Material / Finish
1	Pin Terminal		Brass, Silver Plated
2	Sleeve Shunt		Brass, Silver Plated
3	Sleeve Spring	1	Manganese Steel, Silver Plated
4	Pin		Brass, Tin Plated
5	Housing		PBT

Part Number Table

Description	Part Number
DC Power Jack	SPC21364

Important Notice: This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro

