


# Push Pull Connector IP67 Metal

multicomp<sup>PRO</sup>

RoHS  
Compliant



## Diagram



## Specifications

Dimensions : Millimetres

### Material

Housing (Body)	: Brass, Natural Chrome plated
Insulator	: PPS
Terminal	: Brass, Gold Plated

### Electrical

Voltage Rating	: 250V
Current Rating	: See chart
Dielectric withstanding voltage	: See chart
Electrical Life	: 5,000 Cycles min.

### Temperature Rating

Operating temperature	: -55°C to +150°C
-----------------------	-------------------

### Environmental








IP67 Protection (Mated Condition)


Newark.com/multicomp-pro  
Farnell.com/multicomp-pro  
sg.element14.com/b/multicomp-pro

multicomp<sup>PRO</sup>

# Push Pull Connector IP67 Metal

**multicomp** PRO

	2 Pin	3 Pin	4 Pin	5 Pin	6 Pin	7 Pin	9 Pin
Configuration							
Diameter of Pin	Ø0.9	Ø0.9	Ø0.7	Ø0.7	Ø0.5	Ø0.5	Ø0.5
Testing Voltage	1200V	1200V	1000V	1000V	900V	800V	800V
Working Voltage	250V	250V	200V	200V	200V	200V	200V
Rated Current / Pin	8A	7A	5A	5A	2.5A	2A	2A



## Part Number Table

Description	Position	Part Number
Push Pull Connector Female Plug, 4.2mm to 5.2mm, IP67	2	MCP-M0FG02S52-IP67
	3	MCP-M0FG03S52-IP67
	4	MCP-M0FG04S52-IP67
	5	MCP-M0FG05S52-IP67
	6	MCP-M0FG06S52-IP67
	7	MCP-M0FG07S52-IP67

**Important Notice :** This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/multicomp-pro  
Farnell.com/multicomp-pro  
sg.element14.com/b/multicomp-pro

**multicomp** PRO