

Accessories

Flat nozzle Part No. 197889-6



Extension nozzle Part No. 197888-8



Attach the flat nozzle or extension nozzle to the adapter pipe, and then turn it to lock it into place.

Shoulder strap Part No. 166094-6







Cordless Blower

DUB184





Max Air Volume Max Air Velocity No Load Speed (RPM) Continuous Use (min.) Sound Pressure Level Sound Power Level Vibration Level Dimensions(L x W x H) 13.0 m³/min (459 CFM) 52.1 m/s (116 MPH) 0 - 18,000 w/BL1860B: 12, w/BL1850B: 10 86.6 dB(A) 2.5 m/s² or less w/BL1830B/BL1850B/BL1860B: 825x160x285 mm (32-1/2"x6-5/16"x11-1/4") 2.5 - 3.0 kg (5.4 - 6.7 lbs.)

Standard Equipment: Hex Wrench

The weight may differ depending on the attachment(s), including the battery cartridge. The lightest and heaviest combination, according to EPTA-Procedure 01/2014, are shown in the table. Items of standard equipment and specifications may vary by country or area

Makita Singapore Pte Ltd

7, Changi South Street 3, Singapore 486348 Phone: +65-6546-8700 Fax: +65-6546-8711 Email: msgproductteam@makita.com.sg Website: www.makita.com.sg Facebook: www.facebook.com/MakitaSG







DOWNLOAD LEAFLET

PRINTED IN SINGAPORE

Cordless Blower DUB184





Powerful Cordless Blower Powered by One 18V battery

Max air volume 13.0 m³/min

Thakita

Control lever High

Cruise control and Variable switch

Switch trigger

Max air velocity 52.1

Lightweight [with BL1850B] **KG**



Installing the flat nozzle or extension nozzle (option)

Flat nozzle



Adapter pipe





Lockable speed lever

By locking the lever, you can blow without holding the trigger.

Variable speed trigger

Besides, you can adjust air power as you want by holding the variable







Continuous run time (approx): min

| 18V | 3.0Ah BL1830B | 5 |
|------|---------------|----|
| LXT. | 5.0Ah BL1850B | 10 |
| | 6.0Ah BL1860B | 12 |

On a single full battery charge with max air setting













Hole on the bottom of housing for hanging the machine

