Slide Switches Miniature

multicomp PRO

RoHS Compliant



Specifications

Max. Contact Rating : 0.4 (VA) maximum at 20V maximum (AC or DC)

Mechanical Life : 20,000 cycles

 $\begin{array}{ll} \text{Max. Initial Contact Resistance} & : 50 \text{m}\Omega \\ \text{Min. Insulation Resistance} & : 1,000 \text{M}\Omega \end{array}$

Dielectric Strength : 1,000V RMS at sea level

Operating Temperature : -40°C to +80°C Minimum Load : 10mA, 50mV


Breaking Capacity : 100mA, 30V DC with resistive load


Materials


Case : Nylon, white
Housing : Nylon, black
Actuator : Nylon, black

Contacts / Terminals : Copper alloy, with gold plated


Pole Option









M2RE









Dimensions: Millimetres (Inches)

Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro



Slide Switches Miniature



Soldering Process

Manual Soldering : Use soldering iron of 30 W, controlled at 350°C approximately 5 seconds

while applying solder


Wave Soldering:

Recommended Soldering Temperature : 260 ±5°C

Duration of solder immersion: 5 ±1 seconds (PCB is 1.6 mm in thickness)

Soldering : Vapour phase

Temperature Profile							
Zone	Room Temperature (°C)	Time (Seconds)					
Pre-heat (A)	150°C	Minimum 120					
Soak (B)	180°C to 200°C	Minimum 150					
Peak (C)	200°C to 235°C	Minimum 30					
Peak (D)	235°C to 260°C	Minimum 40					
Peak (E)	260°C	Maximum 10					



Specification Table

Number of	Switch Function		Connected Terminals					
	Position 1	Position 2	Position 3	Position 1	Position 2	Position 3		Model
Poles		4		4	4		Schematic	Number
SP	On	None	On	2 - 1	Open	2 - 3	1 2 (Comm) 2 (Comm) 1 3 1 3	6MS1
DP				2 -1, 5 - 4		2 - 3, 5 - 6	2 (Comm) 2 (Comm) 5 4 6 1 4 8 6	6MD1

Part Number Table

Description	Part Number	
Switch, Slide, SPDT, On-On	6MS1S2M1RE	
Switch, Slide, DPDT, On-On	6MD1S2M2RE	
Switch, Slide, SPDT, On-On	6MS1S4M1RE	
Switch, Slide, DPDT, On-On	6MD1S4M2RE	
Switch, Slide, SPDT, R / A, On-On	6MS1S3M1RE	
Switch, Slide, DPDT, R / A, On-On	6MD1S3M2RE	

Important Notice: This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro

