

Datasheet

RS 6 Digit , LED, Counter, 20kHz, 24 V

RS Stock number 808-6633



INPUTS

Counting Inputs(Ch-A, Ch-B): Switch, proximity, capacitive sensor or encoder can be connected.

Reset Input: Switch, proximity or capacitive sensor can be connected.

Pause Input: Switch, proximity or capacitive sensor can be connected.

Sensor Type Selection: NPN or PNP can be selected,

Reset Function: Automatic or Manual

Count Input Types and Maximum Frequency:

INC, DEC, INC/DEC, INC/INC, UP/DOWN Max. 20kHz.

x1 / x2 / x4: phase shifting (for encoder) counting; Maximum 10kHz.