## M12 Sensor Connector A-Coded, Field-wireable

# multicomp PRO

### Field-wireable connector M12, A-coding, Female, Straight

4

3

Screw

: 250V :4A : ≥10<sup>8</sup>Ω : ≤ 3mΩ : 2500V

IEC 61076-2

PBT

## RoHS Compliant



## **Technical Data**

## Connector

Connector A	:
Number of Pins	:
Contacts	:
Contact Carriers	:
Copling Nut/screw	:
Connector body	:
External diameter of the cable	:
Core cross-section/Clamping ability	:
Connection mode	:
Mechanical lifespan	:
Pollution degree	:
Protection Class	:
Locking mode	:
Standard	:
Electrical properties at +20 °C	

Rated Voltage
Current
Insulation resistance
Forward resistance
Test voltage

### Mechanical and chemical properties

Ambient temperature range

Features

- Metal coupling nut
- Metal housing
- Protection class: IP67
- Screw terminal
- 4-Pin

Brass, Gold-plated

Brass, Nickel-plated Brass, Nickel-plated 4mm to 6mm (PG 7) 0.14 to 0.75mm<sup>2</sup> Screw connection >100 Mating cycles


IP67, (screwed together)

- Cable feedthrough 4mm to 6mm
- PG7 screw-in thread

Female, M12 x 1, Straight, A-coded

Contact assignr	nent

## Diagram



Dimensions : Millimetres

### : -25°C to 85°C

## Part Number Table

Description	Part Number
M12 Sensor Female Connector, A-Coded, 4 Pins	MP011270

Important Notice : This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/multicomp-pro Farnell.com/multicomp-pro sg.element14.com/b/multicomp-pro

