# Temperature Controlled Soldering Station

# multicomp PRO



# RoHS Compliant

# Features

- A temperature controlled soldering station with adjustable temperature range from 160°C to 480°C.
- A two-line LED readout simultaneously displays temperature setting and actual temperature setting and actual temperature.
- · Gloss finish pleasing to the eye.
- · Compact and lightweight soldering iron with silicone cord.
- A user-friendly soldering iron handle with a foam sleeve.
- Easier way to achieve °C/°F conversion with the asterisk button.
- The M button: a preset button for temperature setting. Touch and hold the M button for 2 seconds until the temperature setting flickers. Then touch the button "▲" or "▼" to preset the temperature. Finally touch the M button again to confirm.
- · It comes with soldering iron stand, solder wire stand, solder wire, cleaning sponge and cleaning ball.

# **Specifications**

Heater	: +160°C to +480°C (320°F to 896°F) [High quality coated Heater]
Input Voltage	: AC 110V to 130V, 60Hz or AC 220V to 240V, 50Hz
Output Voltage	: 24V
Power	: 25W (Max. 50W)

# **Soldering Iron Accessories**

1. Spare Soldering Iron for MP740998




## Specifications

Voltage : 24V Power : 25W (Heat up rating 50W) Note: 4 Pins

### 2. High Quality Spare Tips for Soldering Iron






Dimensions : Millimetres

Newark.com/multicomp-pro Farnell.com/multicomp-pro sg.element14.com/b/multicomp-pro



# **Temperature Controlled Soldering Station**



#### **Dimensions : Millimetres**

**multicomp** PRO

#### 3. Spare Heater for MP740998



### **Specifications**

Voltage : 24V Power : 50W

#### 4. Cleaning Sponge

MP-79-7309

### **Specification**

Size

: 25mm × 40mm

### 5. Cleaning Ball For MP740998



MP-87-0134

### Part Number Table

Description	Part Number
Soldering Station, 50W, EU/EK Plug	MP740998
Soldering Iron For MP740998	MP-420
Soldering Tip, Point, OD 1.2mm	MP-N8-1
Soldering Tip, Point, OD 0.6mm	MP-N8-2
Soldering Tip, Cut-Off, 2mm	MP-N8-3
Soldering Tip, Chisel, 2mm	MP-N8-4
Replacement Heater For MP740998	MP-78-4201
Cleaning Sponge, 25mm×40mm	MP-79-7309
Cleaning Ball For MP740998	MP-87-0134

Important Notice : This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/multicomp-pro Farnell.com/multicomp-pro sg.element14.com/b/multicomp-pro

