



Main

Range	Masterpact
Product or component type	Chassis
Type of accessory	Mounting accessory
Product compatibility	Masterpact MTZ2 40 H1 Masterpact MTZ2 40 H1T Masterpact MTZ2 40 H10 Masterpact MTZ2 40 HA Masterpact MTZ2 40 HA10 Masterpact MTZ2 40 H2 Masterpact MTZ2 40 H1b Masterpact MTZ2 40 H3
Poles description	4P
Performance level	H3 H1T H10 HA H1 H1b HA10 H2 HF

Complementary

Mounting mode	Drawout
[In] rated current	4000 A at 40 °C
Height	Chassis alone: 439 mm Drawout circuit breaker with chassis: 439 mm
Width	Chassis alone: 556 mm Drawout circuit breaker with chassis: 556 mm
Depth	Chassis alone: 394 mm Drawout circuit breaker with chassis: 403 mm

Offer Sustainability

Sustainable offer status	Green Premium product
EU RoHS Directive	Compliant EU RoHS Declaration
Mercury free	Yes
RoHS exemption information	Yes
China RoHS Regulation	China RoHS Declaration
Environmental Disclosure	Product Environmental Profile
Circularity Profile	End Of Life Information
WEEE	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins
PVC free	Yes
California proposition 65	WARNING: This product can expose you to chemicals including: DINP, which is known to the State of California to cause cancer, and DIDP, which is known to the State of California to cause birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.