Glass Passivated 3 Phase Bridge Rectifier





Features

- · Glass passivated chip, high reliability
- Low forward voltage drop
- Insulation voltage 2,500V
- · Small size and light weight
- · Small thermal resistance, high thermal conductivity and low temperature rise

Applications

- · Power supply of DC equipment
- · Input rectifier for PWM converter
- DC motor

Maximum Ratings And Electrical Characteristics

Rating at 25°C ambient temperature unless otherwise specified. Single phase, half wave, 60Hz, resistive or inductive load. For capacitive load, derate current by 20%

Characteristic	Symbol	HGBJ3508	HGBJ3510	HGBJ3512	HGBJ3516	Unit	
Voltage Ratings							
Peak Repetitive Voltage	Vrrm	800	1,000	1,200	1,600	V	
Peak Non-Repetitive Reverse Voltage	Vrsm	900	1,100	1,300	1,700		
Forward Conduction							
Maximum Average Forward Rectified Current @Tc = 110°C	lF(AV)	35				A	
Peak Forward Surge Current t=8.3ms at 60Hz	IFSM	400					
I ² t Rating for Fusing	l²t	660				A ² s	
Maximum Forward Voltage drop per element at 25A Peak	VF	1.1			V		
Reverse peak current VR = VRRM @ TJ = 25°C VR = VRRM @ TJ = 150°C	lr	5 3				μA mA	
RMS Isolation Voltage from Case to Lead	Viso	2,500			V		
Typical Thermal Resistance (Note1)	Rөjc	0.8			°C/W		
Mounting torque M3	M _d	0.8			N.m		
Weight	W _t	10			g		
Thermal Characteristics							
Operating Temperature Range	TJ	FE to 1150		°C			
Storage Temperature Range	Тѕтс	-55 to +150					

Notes: 1. Thermal resistance junction to case.

2. The typical data above is for reference only


Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro





Glass Passivated 3 Phase Bridge Rectifier




Rating and Characteristic Curves










Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro



Glass Passivated 3 Phase Bridge Rectifier



Dimension:



Dimensions: Inches (Millimetres)

Part Number Table

Description	Part Number	
	HGBJ3508	
Class Descripted 2 Dhase Bridge Destifier	HGBJ3510	
Glass Passivated 3 Phase Bridge Rectifier	HGBJ3512	
	HGBJ3516	

Important Notice: This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Page <3>

Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro

