



RoHS
Compliant



Features

- Thin In-Line Fuse Holder designed for turn one slot into two.
- Use with ATL MICRO3 fuses from 5A to 15 AMP fuses each slot.
- Butt Splice connectors pull-out force min. 15kg.
- Cable Wire:#16-UL1015 Red Wire-135mm±5mm(5.3").
Applicable Fuse: Micro 3 Fuse

Diagram



AWG	mm	inch	(mm ²)	(Ω/km)	(A)	(A)
16	1.29	0.0508	1.318	13.5	5.2	5.9

Part Number Table

Description	Part Number
Inline Fuse Holder, Micro 3 Blade	MP013623

Dimensions : Millimetres

Important Notice : This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/multicomp-pro
Farnell.com/multicomp-pro
sg.element14.com/b/multicomp-pro