



Overview: Accessory compatibility ew G4 versus Evolution Wireless Digital

Article Name	Article Number	works with ew G4	works with Evolution Wireless Digital
Headmics and lavalier microphones			
ME 2	508935	✓	✓ ¹
ME 2-II	507437	✓	✗
MKE ESSENTIAL OMNI	508249 / 508250	✓	✓
HSP 2-ew	009866	✓	✓
HSP 2-ew-3	009872	✓	✓
SL HEADMIC 1 BE	506272	✓	✓
SL HEADMIC 1 BK	506271	✓	✓
SL HEADMIC 1 SB	506904	✓	✓
ME 3-II	506295	✓	✗
ME 3	508928	✓	✓ ¹
ME 4-N	005020	✓	✗
ME 4	508936	✓	✓ ¹
MKE 1-ew	502876	✓	✓
MKE 1-ew-3	502879	✓	✓
MKE 2-ew GOLD	009831	✓	✓
MKE 2-ew-3 GOLD	009832	✓	✓
MKE 40-ew	500527	✓	✓
HS 2 BE	508882	✓	✓
HS 2 BK	508883	✓	✓
HS 2-ew BE	508531	✓	✗
HS 2-ew BK	508530	✓	✗
HSP 4-ew	009867	✓	✗
HSP 4-ew-3	009873	✓	✗
Microphone capsules			
KK 204	008651 / 008652	✓ 300/500 only	✓ ²
KK 205	008653 / 008654	✓ 300/500 only	✓ ²
MM 435	508829	✓	✓
MM 445	508830	✓	✓
MMD 42-1	506772	✓	✓
MMD 835-1 BK	502575	✓	✓
MMD 845-1 BK	502576	✓	✓
MMD 935-1 BK	502577	✓	✓
MMD 945-1 BK	502579	✓	✓
MME 865-1 BK	502581	✓	✓
MMK 965-1 BK	502582	✓	✓
MMK 965-1 NI	502584	✓	✓
ME 9002	502587	✗	✓
ME 9004	502588	✗	✓
ME 9005	502589	✗	✓
RF accessories			
HALF WAVE DIPOLE	508868-72	✓	✓
ASA 214 UHF	508241	✓	✗
EW-D ASA	508879-81	✓	✓
EW-D ASA CN/ANZ	508998	✓	✓
AB 4	508538-43	✓	✗ ⁵
EW-D AB	508873-78	✗ ³	✓

¹ You can recognize the latest generation of ME 2, ME 3 and ME 4 microphones by its golden connector

² Please note that the capsule rotation mute is not functional with EW-D and G4

³ Compatible with ew G4 if system is tuned within booster range



Article Name	Article Number	works with ew G4	works with Evolution Wireless Digital
ADP UHF ⁴	508863	✓	✓
A 3700	502195	✓	✗ ⁵
AD 3700	502197	✓	✗ ⁵
A 1031-U	004645	✓	✓
A 2003-UHF ⁴	003658	✓	✓
A 5000-CP	USA5000CP	✓	✓
ASP 212	003421	✓	✓
Power supplies			
NT 12-5CW	507352	✓ 100 only	✗
NT 12-5 CW+	508899	✓	✓
NT 12-35 CS	508995	✗	✓
NT 5-20 UCW	508996	✗	✓
Spare parts and rackmounts			
GA 3 Rackmount	503167	✓	✓
CI 1-N	005021	✓	✓
EW-D SK BELT CLIP VERTICAL	508993	✗	✓
ew G4 Beltclip	576130	✓	✗
CI 1-N	005021	✓	✓
CI1REW	USCI1REW	✓	✓
CL 2	004840	✓	✓
SKM-EW ID RINGS COLORED KEN	549344	✓	✗
EW-D COLOR CODING SET	508989	✗	✓
EW-D SK COLOR CODING	508990	✗	✓
EW-D SKM COLOR CODING	508991	✗	✓
EW-D EM COLOR CODING	508992	✗	✓
EW-D EM RUBBER FEET	508994	✓	✓
BA 70	508860	✗	✓
L 70 USB	508861	✗	✓
EW-D CHARGING SET	508862	✗	✓

⁴ ADP UHF is the official successor of A 2003-UHF which will be soon discontinued

⁵ It is not recommended to use this article with Evolution Wireless Digital systems