


## Reprogramming Wireless Remote Control for Rocker Switch Start/Stop Generators



Bulletin number # 2030003

This bulletin covers the following Champion Power Equipment models (*Note: Read instructions completely before performing service*):

– **All Champion Power Equipment**

NOTE: Read instructions completely before performing service.

1. Turn the front panel engine switch ON (middle position).
2. Turn the battery switch ON.
3. Push and hold the programming button on left side of the panel next to the red light (located on the back left side of the panel) approximately three seconds until the light turns on.
4. Push and release the STOP button on the remote. The red light blinks once to erase the remote program. *If you have a second remote, press the STOP button on it as well.*
5. Push and release the START button. The red light blinks once to program the remote. *If you have a second remote, press the START button on it as well.*
6. Push and hold the programming button approximately three seconds until the red light turns off.

If you have any questions regarding the previous procedure, please contact our technical department Monday-Friday from 8:30 AM-5:00 PM PST at 877-338-0999.

If you have any questions, please contact Champion Power Equipment:

Champion Power Equipment, Inc.  
12039 Smith Ave.  
Santa Fe Springs, CA 90670

Phone: 1-877-338-0999

Email: [tech@championpowerequipment.com](mailto:tech@championpowerequipment.com)