

Reprogramming Wireless Remote Control for Automotive Style Push-Button Generators



Bulletin number # 2030004

This bulletin covers the following Champion Power Equipment models (*Note: Read instructions completely before performing service*):

– **All Champion Power Equipment**

NOTE: Read instructions completely before performing service.

Generator MUST be completely OFF. No lights showing on push-button engine switch.

1. Press push-button engine switch. Push-button will flash orange.
2. Locate the red programming button on the back side of the control panel.
3. Push and hold the red programming button for approximately 3 seconds until the push-button engine switch stops flashing. Switch will show solid orange.
4. Push and release the STOP button on the remote to erase the remote program. Push-button will briefly turn green.
5. Push and release the START button on the remote to program the remote. Push-button will briefly turn green.
6. Push and hold the red programming button for approximately 3 seconds until the push-button engine switch starts flashing orange again.

The remote is now programmed to start and stop the generator from an unobstructed distance of up to 80 feet (24m). Refer to generator Operator's Manual for complete starting and stopping instructions.

If you have any questions regarding the previous procedure, please contact our technical department Monday-Friday from 8:30 AM-5:00 PM PST at 877-338-0999.

If you have any questions, please contact Champion Power Equipment:

Champion Power Equipment, Inc.
12039 Smith Ave.
Santa Fe Springs, CA 90670

Phone: 1-877-338-0999

Email: tech@championpowerequipment.com