



LogiLink_®

German Wall Outlet with 2 USB Ports

1x USB-C & 1x USB-A port

Art. No.: **PA0262 PA0262W**



Space-saving & Charging Your Devices Directly

This easy-to-install German wall socket with integrated 2 USB ports enable space-saving electrical installation and provide a new energy without having to occupy the socket with an additional charger. It's great for cafés, hairdressing salons, hotels or, of course, in your own walls at home or in the office – wherever you need new energy for your smartphone or tablet quickly.







2 USB ports can charge up to two devices simultaneously, such as smartphone, tablet, mobile power supply, MP3, digital camera, etc.



The USB German socket fits in standard flush-mounted socket.



Quickly charge with USB outputs.








2 USB Outputs: 5 V/2.8 A,

AC socket load: 16 A, 3600 W max.

14 W max.





How to Install:










- a. Turn power off before connecting and check that no voltage is present.
- b. Connect the wires and install the base into the wall.

 There are 2 ways to install, fix the base with screw (A) or claw (B).
- c. Install the panel and screw the socket onto the receptacle.







Art-No.	Color	EAN Code
PA0262	White	4052792063066
PA0262B	Black	4052792078602







Specifications:

Rated Voltage	230 V AC 50/60 Hz, 0.25 A	
Max. Power	USB-A+USB-C: 5 V/2.8 A (14 W) AC outlet: 16 A, 3600 W	
Standby Power Consumption	0.09 W	
Operating Temperature	0-35°C	
Operating Humidity	40–75%	
Storage Temperature	-10-50°C	
Storage Humidity	10-80%	
Dimensions	8 x 8 x 3.8 cm	
Weight	0.11 kg	

Package Contents:

- » 1x German Wall Outlet with 2-USB Port
- » 1x User Manual

Package Information:

» Packing Dimension: 115 x 82 x 30 mm

» Packing Weight: 0.115 kg

» Carton Dimension: 485 x 355 x 240 mm

» Carton Q'ty: 100 pcs » Carton Weight: 14 kg



^{*}For indoor use only.

^{*}Use only in dry areas.
*The installation and assembly of electrical devices may only be carried out by a qualified electrician!