

VR11

GNSS RECEIVER



VertexNav The Power Of Precision

PPP

Precise point precision

10000 mAh




Up to 20 hours
Operating time



IMU

Tilt compensation



1408 Channels



VERTEX
NAVIGATION SOLUTIONS

VR11 GNSS RECEIVER

Specifications

GNSS Performance

Channels	1408 channels
GPS	L1, L2, L5
GLONASS	L1, L2
Galileo	E1, E5a, E5b
BeiDou	B1I, B2I, B3I, B1C, B2a
QZSS	L1, L2, L5
PPP	B2B ,E6_has

GNSS Accuracies

Real time kinematics(RTK)	Horizontal: 8 mm + 1 ppm RMS Vertical: 15 mm + 1 ppm RMS Initialization time:< 5s Initialization reliability: > 99.9%
Post-processing kinematics (PPK)	Horizontal: 2.5 mm + 1 ppm RMS Vertical: 5 mm + 1 ppm RMS
Post -processing static	Horizontal: 2.5 mm + 0.5 ppm RMS Vertical: 5 mm + 0.5 ppm RMS
Time to first fix	Cold start: <25 s Hot start: < 10 s Signal re-acquisition: < 1s

Hardware

Size (L x W x H)	140 mm x 140 mm x 88 mm (5.5 in x 5.5 in x 3.5 in)
Weight	1.03 kg (2.27lb)
Environment	Operating: -45°C to +75°C (-49°F to +167°F) Storage: -55°C to +85° (-67°F to +185°F)
Humidity	100% condensation
Ingress protection	IP67 waterproof and dustproof, protected from temporary immersion- to depth of 2 m
Shock	Survive a 2- meter pole drop
Front panel	4 LED indicates 2 physical buttons

*The above technical parameters are subject to the actual product; any changes will be made without further notice.

Communication

Bluetooth	v 4.0, Backward compatible with BT2.x
Ports	1 x 9 PIN aviation plug, including power supply, COM RS232, CONFIG, RS232. 1 x UHF radio antenna interface Web Interface
	Standard Internal Rx / Tx : 410 -470 MHz Transmit Power: 0.5 W to 2 W Protocol: Transparent, TT450S,Trintalk, TRMMARK3 Range: Typical 5 km to 8 km
Data formats	RTCM2.x, RTCM3.x, CMR
Data storage	8 GB internal memory

Electrical

Power consumption	5 W (depending on user settings)
Li -ion battery capacity	10000mAh
Operating time on internal battery	20h (Rover) 10h (Base)
External power input	9 V DC to 36 V DC
Power consumption	As Rover<4.0W As Base<10.5W



VertexNav Dealer Partner Area

Visit our website to learn more about our products: www.vertexnav.com