

BLV6F



Band III antenna with F connector, 6 elements.

High **gain**, optimum impedance adaptation and excellent directivity.

Exclusive Fracarro design

- Band III antennas with F connector
- High quality pre-assembled and with zenithal adjustment as standard
- High gain, excellent impedance matching and excellent directivity
- It guarantees exceptional durability of electrical and mechanical qualities
- Exclusive design patented by Fracarro

		BLV6F
Code		218058
Elements	no.	6
Band		3
Channel		E5-E12
Bandwidth	MHz	174-230
Gain	dBi	13
Front/Back ratio	dB	24
Return loss	dB	-22
Beam width (-3dB)	°	±24
Wind load at 120km/h (720N/m ²)	kg (N)	4.5 (44.14)
Connector	Type	F
Impedance	Ω	75
Max mast (Ø)	mm	60
Dimensions (L x H)	cm	149 x 87
Quantity Master box	pcs	3
Unit weight	kg	2
Total weight	kg	6.7

Accessories

Horizontal polarization	Included
Horizontal polarization Tilt adjustment	Included
Vertical polarization	PV10 (210011)
Vertical polarization Tilt adjustment	PV10 (210011)
Auxiliary boom	N/A