AMBA - THE COMPACT POWERFUL

With the capacity for an internal capture card and a removable drive; the Hippotizer Amba outper-forms many larger systems.

With a single unlimited resolution output, the Hippotizer Amba can be used with splitters or on greater than HD projects.

Size (mm) L/W/H Size (mm) L/W/H With Rack ears Size (RU) Unit Weight Power Input Voltage Power Consumption Mounting Rack Drawer Compatable?

HIPPVTIZER

AMBA

475/425/45 500/480/45 1U 8Kgs IEC 100-250V 50/60Hz Auto Sense 350VA Front and Rear Ears Included Yes

Ð

 \odot \odot \odot \odot

2 = 0

D

ZooKeene



Camera Inputs

ONE OUTPUT

Output Specifications Production Video Outputs Production Output Connector Max Resolution per DP output Video Splitter Support Additional Control outputs (ZK) Genlock AMBA DP 1 1 x DP 1.2 4096 x 2160 Yes 2x DVI, 1x DP 1.2 No

Software Specs	
Max mixes	4
Layers per Mix	16
4K playback*	upto 2
HD playback*	upto 8
Software Update Period****	3 Years

Hardware Specs Video Capture**** Media Storage Media Storage Speed HippoNet Network Data Network Audio Input Connections Audio Output Connections MultiChannel Audio Support Hardware EDID Management Software EDID Management

Optional Touch Screen Optional Redundant PSU SMPTE Timecode In Yes: 1 Card 500GB Solid State 400 MB/s 1Gb Cat 5 1Gb Cat 5 3.5mm Stereo 3.5mm Stereo Via USB

Yes

Optional

*Please see the website for full technical specifications

Learn how to Play, encode, pre-program, visualise and learn for free with the award winning media server software. Hippotizer PLAY will allow you to visualise the possibilities with all the key features and components of Hippotizer Media Servers.

www.green-hippo.com/play-licensing

ACCESSORIES

STRATA Caddy Drive 480Gb STRATA Caddy Drive 900Gb Extra power lead Additional Input Card Cables 10GB HippoNet upgrade Flight Case

Input cards Dual SDI AV-SDI (SDI / Composite / DVI) Dual DVI 10Gig NIC (HippoNet) SMPTE IN card

