

DIMMING RECOMMENDATIONS

10W (DIMMABLE)

DaxBUD, DaxPRO, DaxELITE & DaxTILT

Please Note: On occasions a selection of modules from the below list may have to be used on a single property to overcome interference with electrical appliances within the property e.g. non emc compliant luminaires or appliances. This information is correct at the time of issue and results may be different under actual field conditions and is subject to change either by DaxLite Ltd or the manufacturer of the dimmer modules outlined in this document. If you have any further questions regarding the dimming of the new DaxPRO please contact our technical department for further advice.

DaxLite

DaxLite Limited
17A Blackwater Trading Estate
Blackwater Way, ALdershot,
Hampshire, GU12 4DN

Tel: 01252 311016
Fax: 01252 330821
Email: sales@daxlite.com
Web: www.daxlite.com

DIMMER TYPE-MODEL NUMBER	LOADING COMMENTS	DIMS DOWN TO %
AURORA AU-DSP400 60-400W	LOADING x 1-20 LUMINAIRES	DIMS TO 5%
CLICK CMA140 60-400W	LOADING x 2-20 LUMINAIRES	DIMS TO 10%
CLICK MD9042 60-400W	LOADING x 2-20 LUMINAIRES	DIMS TO 10%
CLICK ML111 40-250W	LOADING x 2-20 LUMINAIRES	DIMS TO 5%
CLICK PRW140 60-400W	LOADING x 2-20 LUMINAIRES	DIMS TO 10%
DANLERS DQDGMK 400W	LOADING x 1-20 LUMINAIRES	DIMS TO 10%
HAMILTON 741X100 LED 100W	LOADING x 1-10 LUMINAIRES	DIMS TO 10%
HAMILTON KP1X60 600W	LOADING x 1-20 LUMINAIRES	DIMS TO 10%
HAMILTON N4002 400W	LOADING x 1-20 LUMINAIRES	DIMS TO 10%
HAMILTON SMG600 600W	LOADING x 1-20 LUMINAIRES	DIMS TO 10%
HERITAGE BC RANGE 60-400W	LOADING x 1-20 LUMINAIRES	DIMS TO 5%
HERITAGE CR RANGE 60-400W	LOADING x 1-20 LUMINAIRES	DIMS TO 5%
HERITAGE 168J279 400W	LOADING x 2-20 LUMINAIRES	DIMS TO 5%
HERITAGE 398J145 400W	LOADING x 1-20 LUMINAIRES	DIMS TO 5%
MK K1501WHILV 60-500W	LOADING x 1-20 LUMINAIRES	DIMS TO 10%
MK1523WHILV 300W	LOADING x 1-20 LUMINAIRES	DIMS TO 10%
MK4511WHILV 220W	LOADING x 1-20 LUMINAIRES	DIMS TO 10%
ROBUS L2501G2W 40-250W	LOADING x 1-20 LUMINAIRES	DIMS TO 5%
SCHNEIDER GU6012 400W	LOADING x 1-20 LUMINAIRES	DIMS TO 5%
VARILIGHT Z0JP250-P 250W	LOADING x 1-20 LUMINAIRES	DIMS TO 5%
VARILIGHT EQ3W 500W	LOADING x 1-20 LUMINAIRES	DIMS TO 10%
VARILIGHT EQPA 1000W	LOADING x 1-20 LUMINAIRES	DIMS TO 10%
VARILIGHT JPQ401 400W	LOADING x 1-20 LUMINAIRES	DIMS TO 5%
ZANO ZGRID500 500W	LOADING x 1-20 LUMINAIRES	DIMS TO 10%

DaxLite reserves the right to withdraw, improve or modify any design without prior notification. DaxLite cannot be held responsible for the incorrect application of any product.

Company Registration Number: 7955361 VAT Number: 134182827