

Cisco SPA 501 – IVR Configuration Menu

When setting up a Cisco SPA501, it does not have an on screen display so a voice menu is provided to setup the device.

Press the menu button to bring up the voice setup menu

Function	Code
Access IVR	****
Announce WAN IP address	110
Control WAN port admin web server [1 to enable, 0 disable]	7932
Reset to ITSP defaults	877778
Factory reset	73738 [R-E-S-E-T]
Exit IVR	3948 [E-X-I-T]
Announce DHCP	100
Enable DHCP [0 for DHCP, 1 for static IP, 3 for PPPoE]	101
Set WAN port static IP address [* for period, disable DHCP first]	111
Announce WAN netmask	120
Set WAN netmask [* for period, disable DHCP first]	121
Announce WAN gateway IP address [* for period, disable DHCP first]	130
Set WAN gateway IP address [* for period, disable DHCP first]	131
Announce MAC address	140
Announce firmware version	150
Announce primary DNS IP address	160
Set primary DNS server IP address [* for period, disable DHCP first]	161
Announce admin web server WAN port	170
Reboot the device	732668 [R-E-B-O-O-T]